

ANTARI HZ-1000™		
DMX Channel Values / Functions (2 DMX Channels)		
Features are subject to change without any prior written notice.		
CHANNEL	VALUE	FUNCTION
1		HAZE OUTPUT LEVEL
	0-5	HAZE OFF
	6-127	HAZE OUTPUT LOW
	128-255	HAZE OUTPUT HIGH
2		FAN OUTPUT LEVEL
	0-5	FAN 20%
	6-255	FAN 21% - 100%

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
 323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com