

Eliminator® LIGHTING



EX-6

CAUTION! Please read and understand these instructions before installing or operating this unit.

Operating Instructions: The unit is ready to be hung or set on flat surface. This fixture is designed to operate as a stand alone unit. It has been tested and the lamp has been installed at the factory there is no assembly necessary. The EX-6 has three different operating modes. For best results, we suggest using fog or special effects smoke when using this unit. This will enhance the effect allowing you to see the beams of light.

This unit comes with a 3-way multi-operating switch located on the rear of the unit. The switch controls three (3) different operating modes; Static, Sound Active, and Continuous Rotation. When the switch is in the "I" position the internal dichroic dish spin continuously and the barrel mirror will react to sound, via its internal microphone. When the unit is in the "0" position the internal dichroic dish is static (does not rotate) and the barrel mirror will react to sound. When the switch is in the "II" position the unit's internal dichroic color wheel and barrel mirror will react to sound.

SPECIFICATIONS:

Model:	EX-6
Weight:	6 lbs./2.8Kgs.
Size:	19"H x 9"W x 10"L
Lamp:	LL FCR 12V 100W
Fuse:	3A
Supply Voltage:	120V
Working Position:	Any Safe position
Colors:	Multiple Colors
Duty Cycle:	15min on/off
Warranty:	1 Year

Caution! Never open unit when in use. Always disconnect main power before serving or replacing lamp. Remember to always replace with the exact same type lamp and fuse.

HALOGEN LAMP WARNING!

This fixture is fitted with halogen lamps which are highly susceptible to damage if improperly handled. Never touch lamp with bare fingers as the oil from your hands will shorten lamp life. Also, never move fixture until lamp has had ample time to cool. Remember, lamps are not covered under warranty conditions.

Lamp Replacement: Remove the two thumb screws located on the bottom of the unit. Gently, remove the lamp access trap door to access the lamp. Remove and replace the bad lamp and reassemble in reverse order.

1 Year Limited Warranty: Eliminator Lighting warranty is valid from the date of purchase. Our 1 year limited warranty covers manufacturing defects only. Serial number, place of purchase with dated valid receipt must be submitted at time of service. Eliminator Lighting warranty does not cover items or parts prone to wear and tear: lamps, fuses, brushes and belts. Eliminator Lighting warranty is only valid with-in the United States.