

ADJ JOLT PANEL FX - DMX TRAITS

DMX TRAITS: 6 CHANNEL MODE

Features subject to change without notice		
6 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Outer Red: 0 to 100%
2	000-255	Outer Green: 0 to 100%
3	000-255	Outer Blue: 0 to 100%
4	000-255	Inner White: 0 to 100%
5	000-255	Dimmer: 0 to 100%
6	000-255	Dimmer Fine: 0 to 100%

DMX TRAITS: 9 CHANNEL MODE

Features subject to change without notice		
6 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Outer Red: 0 to 100%
2	000-255	Outer Green: 0 to 100%
3	000-255	Outer Blue: 0 to 100%
4	000-255	Inner White: 0 to 100%
5	000-255	Dimmer: 0 to 100%
6	000-255	Dimmer Fine: 0 to 100%
7		Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
8	000-255	Strobe Rate: Slow to Fast
9	000-255	Strobe Duration: Slow to Fast

DMX TRAITS: 13 CHANNEL MODE

Features subject to change without notice		
13 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Outer Red: 0 to 100%
2	000-255	Outer Green: 0 to 100%
3	000-255	Outer Blue: 0 to 100%
4	000-255	Inner White: 0 to 100%
5	000-255	Outer Color Macros
6	000-255	Dimmer: 0 to 100%
7	000-255	Dimmer Fine: 0 to 100%
8		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
9	000-255	Outer Strobe Rate: Slow to Fast
10	0-255	Outer Strobe Duration: Slow to Fast

DMX TRAITS: 13 CHANNEL MODE

Features subject to change without notice		
13 CHANNEL MODE	VALUE	FUNCTION
11		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
	126-135	Macro13
	136-145	Macro14
	146-155	Macro15
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
	236-245	Macro24
246-255	Macro25	
12		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
	201-228	Macro8
229-255	Macro9	
13	000-255	In/Out Program Macro Speed: Slow to Fast

DMX TRAITS: 18 CHANNEL MODE

Features subject to change without notice

18 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Outer Red: 0 to 100%
2	000-255	Outer Green: 0 to 100%
3	000-255	Outer Blue: 0 to 100%
4	000-255	Outer Color Macros
5	000-255	Outer Dimmer: 0 to 100%
6	000-255	Outer Dimmer Fine: 0 to 100%
7		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
8	000-255	Outer Strobe Rate: Slow to Fast
9	0-255	Outer Strobe Duration: Slow to Fast
10		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
	126-135	Macro13
	136-145	Macro14
	146-155	Macro15
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
236-245	Macro24	
246-255	Macro25	
11	0-255	Outer Program Macro Speed
12	000-255	Inner Dimmer: 0 to 100%
13	000-255	Inner Dimmer Fine: 0 to 100%

DMX TRAITS: 18 CHANNEL MODE

Features subject to change without notice

18 CHANNEL MODE	VALUE	FUNCTION
14		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
15	000-255	Inner Strobe Rate: Slow to Fast
16	000-255	Inner Strobe Duration: Slow to Fast
17		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
	201-228	Macro8
229-255	Macro9	
18	000-255	Inner Program Macro Speed

DMX TRAITS: 36 CHANNEL MODE

Features subject to change without notice

36 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Outer Dimmer: 0 to 100%
26	000-255	Outer Dimmer Fine: 0 to 100%
27		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	
28	000-255	Outer Strobe Rate: Slow to Fast
29	000-255	Outer Strobe Duration: Slow to Fast
30	000-255	Inner White Group 1
31	000-255	Inner White Group 2
32	000-255	Inner Dimmer: 0 to 100%
33	000-255	Inner Dimmer Fine: 0 to 100%
34		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	
35	000-255	Inner Strobe Rate: Slow to Fast
36	000-255	Inner Strobe Duration: Slow to Fast

DMX TRAITS: 41 CHANNEL MODE

Features subject to change without notice

41 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Outer Color Macros
26	000-255	Outer Dimmer: 0 to 100%
27	000-255	Outer Dimmer Fine: 0 to 100%
28		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
29	000-255	Outer Strobe Rate: Slow to Fast
30	000-255	Outer Strobe Duration: Slow to Fast

DMX TRAITS: 41 CHANNEL MODE

Features subject to change without notice

41 CHANNEL MODE	VALUE	FUNCTION
		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
31	126-135	Macro13
	136-145	Macro14
	146-155	Macro15
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
	236-245	Macro24
	246-255	Macro25
32	000-255	Outer Program Macro Speed
33	000-255	Inner White Group 1
34	000-255	Inner White Group 2
35	000-255	Inner Dimmer: 0 to 100%
36	000-255	Inner Dimmer Fine: 0 to 100%
		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
37	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
38	000-255	Inner Strobe Rate: Slow to Fast
39	000-255	Inner Strobe Duration: Slow to Fast
		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
40	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
	201-228	Macro8
	229-255	Macro9
41	000-255	Inner Program Macro Speed

DMX TRAITS: 51 CHANNEL MODE

Features subject to change without notice

51 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Red 9
26	000-255	Green 9
27	000-255	Blue 9
28	000-255	Red 10
29	000-255	Green 10
30	000-255	Blue 10
31	000-255	Outer Color Macros
32	000-255	Outer Dimmer: 0 to 100%
33	000-255	Outer Dimmer Fine: 0 to 100%
34		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	
35	000-255	Outer Strobe Rate: Slow to Fast
36	000-255	Outer Strobe Duration: Slow to Fast

DMX TRAITS: 51 CHANNEL MODE

Features subject to change without notice

51 CHANNEL MODE	VALUE	FUNCTION
37		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
	126-135	Macro13
	136-145	Macro14
	146-155	Macro15
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
236-245	Macro24	
246-255	Macro25	
38	000-255	Outer Program Macro Speed
39	000-255	White 1
40	000-255	White 2
41	000-255	White 3
42	000-255	White 4
43	000-255	White 5
44	000-255	White 6
45	000-255	Inner Dimmer: 0 to 100%
46	000-255	Inner Dimmer Fine: 0 to 100%
47		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	

DMX TRAITS: 51 CHANNEL MODE

Features subject to change without notice		
51 CHANNEL MODE	VALUE	FUNCTION
48	000-255	Inner Strobe Rate: Slow to Fast
49	000-255	Inner Strobe Duration: Slow to Fast
50		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
	201-228	Macro8
	229-255	Macro9
51	000-255	Inner Program Macro Speed

DMX TRAITS: 81 CHANNEL MODE

Features subject to change without notice

81 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Red 9
26	000-255	Green 9
27	000-255	Blue 9
28	000-255	Red 10
29	000-255	Green 10
30	000-255	Blue 10
31	000-255	Red 11
32	000-255	Green 11
33	000-255	Blue 11
34	000-255	Red 12
35	000-255	Green 12
36	000-255	Blue 12
37	000-255	Red 13
38	000-255	Green 13
39	000-255	Blue 13
40	000-255	Red 14
41	000-255	Green 14
42	000-255	Blue 14

DMX TRAITS: 81 CHANNEL MODE

Features subject to change without notice

81 CHANNEL MODE	VALUE	FUNCTION
43	000-255	Red 15
44	000-255	Green 15
45	000-255	Blue 15
46	000-255	Red 16
47	000-255	Green 16
48	000-255	Blue 16
49	000-255	Red 17
50	000-255	Green 17
51	000-255	Blue 17
52	000-255	Red 18
53	000-255	Green 18
54	000-255	Blue 18
55	000-255	Red 19
56	000-255	Green 19
57	000-255	Blue 19
58	000-255	Red 20
59	000-255	Green 20
60	000-255	Blue 20
61	000-255	Outer Color Macros
62	000-255	Outer Dimmer: 0 to 100%
63	000-255	Outer Dimmer Fine: 0 to 100%
64		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
65	000-255	Outer Strobe Rate: Slow to Fast
66	000-255	Outer Strobe Duration: Slow to Fast
67		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
	126-135	Macro13
	136-145	Macro14
146-155	Macro15	

DMX TRAITS: 81 CHANNEL MODE

Features subject to change without notice

81 CHANNEL MODE	VALUE	FUNCTION
67		Outer Program Macro
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
	236-245	Macro24
246-255	Macro25	
68	000-255	Outer Program Macro Speed
69	000-255	White 1
70	000-255	White 2
71	000-255	White 3
72	000-255	White 4
73	000-255	White 5
74	000-255	White 6
75	000-255	Inner Dimmer: 0 to 100%
76	000-255	Inner Dimmer Fine: 0 to 100%
77		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	
78	000-255	Inner Strobe Rate: Slow to Fast
79	000-255	Inner Strobe Duration: Slow to Fast
80		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
	201-228	Macro8
229-255	Macro9	
81	0-255	Inner Program Macro Speed

DMX TRAITS: 126 CHANNEL MODE

Features subject to change without notice

126 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Red 9
26	000-255	Green 9
27	000-255	Blue 9
28	000-255	Red 10
29	000-255	Green 10
30	000-255	Blue 10
31	000-255	Red 11
32	000-255	Green 11
33	000-255	Blue 11
34	000-255	Red 12
35	000-255	Green 12
36	000-255	Blue 12
37	000-255	Red 13
38	000-255	Green 13
39	000-255	Blue 13
40	000-255	Red 14
41	000-255	Green 14
42	000-255	Blue 14

DMX TRAITS: 126 CHANNEL MODE

Features subject to change without notice

126 CHANNEL MODE	VALUE	FUNCTION
43	000-255	Red 15
44	000-255	Green 15
45	000-255	Blue 15
46	000-255	Red 16
47	000-255	Green 16
48	000-255	Blue 16
49	000-255	Red 17
50	000-255	Green 17
51	000-255	Blue 17
52	000-255	Red 18
53	000-255	Green 18
54	000-255	Blue 18
55	000-255	Red 19
56	000-255	Green 19
57	000-255	Blue 19
58	000-255	Red 20
59	000-255	Green 20
60	000-255	Blue 20
61	000-255	Red 21
62	000-255	Green 21
63	000-255	Blue 21
64	000-255	Red 22
65	000-255	Green 22
66	000-255	Blue 22
67	000-255	Red 23
68	000-255	Green 23
69	000-255	Blue 23
70	000-255	Red 24
71	000-255	Green 24
72	000-255	Blue 24
73	000-255	Red 25
74	000-255	Green 25
75	000-255	Blue 25
76	000-255	Red 26
77	000-255	Green 26
78	000-255	Blue 26
79	000-255	Red 27
80	000-255	Green 27
81	000-255	Blue 27
82	000-255	Red 28
83	000-255	Green 28
84	000-255	Blue 28

DMX TRAITS: 126 CHANNEL MODE

Features subject to change without notice

126 CHANNEL MODE	VALUE	FUNCTION
85	000-255	Red 29
86	000-255	Green 29
87	000-255	Blue 29
88	000-255	Red 30
89	000-255	Green 30
90	000-255	Blue 30
91	000-255	Red 31
92	000-255	Green 31
93	000-255	Blue 31
94	000-255	Red 32
95	000-255	Green 32
96	000-255	Blue 32
97	000-255	Red 33
98	000-255	Green 33
99	000-255	Blue 33
100	000-255	Red 34
101	000-255	Green 34
102	000-255	Blue 34
103	000-255	Red 35
104	000-255	Green 35
105	000-255	Blue35
106	000-255	Red 36
107	000-255	Green 36
108	000-255	Blue 36
109	000-255	Red 37
110	000-255	Green 37
111	000-255	Blue 37
112	000-255	Red 38
113	000-255	Green 38
114	000-255	Blue 38
115	000-255	Red 39
116	000-255	Green 39
117	000-255	Blue 39
118	000-255	Red 40
119	000-255	Green 40
120	000-255	Blue 40
121	000-255	White 1
122	000-255	White 2
123	000-255	White 3
124	000-255	White 4
125	000-255	White 5
126	000-255	White 6

DMX TRAITS: 141 CHANNEL MODE

Features subject to change without notice

141 CHANNEL MODE	VALUE	FUNCTION
1	000-255	Red1
2	000-255	Green1
3	000-255	Blue1
4	000-255	Red2
5	000-255	Green2
6	000-255	Blue2
7	000-255	Red3
8	000-255	Green3
9	000-255	Blue3
10	000-255	Red4
11	000-255	Green4
12	000-255	Blue4
13	000-255	Red5
14	000-255	Green5
15	000-255	Blue5
16	000-255	Red6
17	000-255	Green6
18	000-255	Blue6
19	000-255	Red7
20	000-255	Green7
21	000-255	Blue7
22	000-255	Red8
23	000-255	Green8
24	000-255	Blue8
25	000-255	Red 9
26	000-255	Green 9
27	000-255	Blue 9
28	000-255	Red 10
29	000-255	Green 10
30	000-255	Blue 10
31	000-255	Red 11
32	000-255	Green 11
33	000-255	Blue 11
34	000-255	Red 12
35	000-255	Green 12
36	000-255	Blue 12
37	000-255	Red 13
38	000-255	Green 13
39	000-255	Blue 13
40	000-255	Red 14
41	000-255	Green 14
42	000-255	Blue 14

DMX TRAITS: 141 CHANNEL MODE

Features subject to change without notice

141 CHANNEL MODE	VALUE	FUNCTION
43	000-255	Red 15
44	000-255	Green 15
45	000-255	Blue 15
46	000-255	Red 16
47	000-255	Green 16
48	000-255	Blue 16
49	000-255	Red 17
50	000-255	Green 17
51	000-255	Blue 17
52	000-255	Red 18
53	000-255	Green 18
54	000-255	Blue 18
55	000-255	Red 19
56	000-255	Green 19
57	000-255	Blue 19
58	000-255	Red 20
59	000-255	Green 20
60	000-255	Blue 20
61	000-255	Red 21
62	000-255	Green 21
63	000-255	Blue 21
64	000-255	Red 22
65	000-255	Green 22
66	000-255	Blue 22
67	000-255	Red 23
68	000-255	Green 23
69	000-255	Blue 23
70	000-255	Red 24
71	000-255	Green 24
72	000-255	Blue 24
73	000-255	Red 25
74	000-255	Green 25
75	000-255	Blue 25
76	000-255	Red 26
77	000-255	Green 26
78	000-255	Blue 26
79	000-255	Red 27
80	000-255	Green 27
81	000-255	Blue 27
82	000-255	Red 28
83	000-255	Green 28
84	000-255	Blue 28
109	000-255	Red 29
110	000-255	Green 29
111	000-255	Blue 29

DMX TRAITS: 141 CHANNEL MODE

Features subject to change without notice

141 CHANNEL MODE	VALUE	FUNCTION
112	000-255	Red 30
113	000-255	Green 30
114	000-255	Blue 30
115	000-255	Red 31
116	000-255	Green 31
117	000-255	Blue 31
118	000-255	Red 32
119	000-255	Green 32
120	000-255	Blue 32
121	000-255	Outer Color Macros
122	000-255	Outer Dimmer: 0 to 100%
123	000-255	Outer Dimmer Fine: 0 to 100%
124		Outer Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
	201-255	Random
125	000-255	Outer Strobe Rate: Slow to Fast
126	000-255	Outer Strobe Duration: Slow to Fast
127		Outer Program Macro
	0-5	No function
	6-15	Macro1
	16-25	Macro2
	26-35	Macro3
	36-45	Macro4
	46-55	Macro5
	56-65	Macro6
	66-75	Macro7
	76-85	Macro8
	86-95	Macro9
	96-105	Macro10
	106-115	Macro11
	116-125	Macro12
	126-135	Macro13
	136-145	Macro14
	146-155	Macro15
	156-165	Macro16
	166-175	Macro17
	176-185	Macro18
	186-195	Macro19
	196-205	Macro20
	206-215	Macro21
	216-225	Macro22
	226-235	Macro23
236-245	Macro24	
246-255	Macro25	

DMX TRAITS: 141 CHANNEL MODE

Features subject to change without notice

141 CHANNEL MODE	VALUE	FUNCTION
128	000-255	Outer Program Macro Speed
129	000-255	White 1
130	000-255	White 2
131	000-255	White 3
132	000-255	White 4
133	000-255	White 5
134	000-255	White 6
135	000-255	Inner Dimmer: 0 to 100%
136	000-255	Inner Dimmer Fine: 0 to 100%
137		Inner Strobe Effect
	0-2	Open
	3-5	Strobe
	6-50	Ramp up
	51-100	Ramp down
	101-150	Ramp up-down
	151-200	Lightning
201-255	Random	
138	000-255	Inner Strobe Rate: Slow to Fast
139	000-255	Inner Strobe Duration: Slow to Fast
140		Inner Program Macro
	0-5	No function
	6-33	Macro1
	34-60	Macro2
	61-88	Macro3
	89-116	Macro4
	117-144	Macro5
	145-172	Macro6
	173-200	Macro7
201-228	Macro8	
229-255	Macro9	
141	000-255	Inner Program Macro Speed