

OCTO BEAM RGBW™



The ADJ Octo Beam RGBW produces a classic disco lighting beam effect with a modern LED twist! This 8-head Beam effect is powered by two red, two green, two blue and two white 3-Watt LEDs. It produces sharp, bright beams at a 3.4 degree beam angle.

The Octo Beam RGBW has 3 DMX channel modes (1, 8 or 10), 3 operational modes (Sound Active, Show or DMX modes), LED pulse and strobe effects and 0-100% electronic dimming.

The rear control panel features a 4-button LED display menu, 3-pin DMX In/Out connections and IEC In/Out for power linking up to 12 units at 120V or 19 units at 230V operation. This fixture is compatible with the ADJ UC3 easy-to-use controller.

Specifications:

- 8-head Beam Effect with 8x 3W RGBW LEDs (2 Red, 2 Green, 2 Blue & 2 White)
- 3 DMX Channel modes: 1, 8 or 10 channel modes
- 3 Operational modes: Sound Active Mode, Show Mode, & DMX Controlled
- Stand Alone or Master-Slave Configuration
- LED pulse & strobe effect
- Flicker Free
- Electronic Dimming: 0 - 100%
- Beam angle: 3.4-degree
- Linkable via 3-pin XLR cable
- 4-button LED display on rear panel
- IEC AC IN/OUT on rear to daisy chain power (up to 12 Octo Beam RGBW's @ 120V and 19 Octo Beam RGBW's @ 230V)
- Compatible with American DJ UC3 Series easy-to-use controllers (sold Separately)
- Includes mounting yoke to mount on a wall or on to trussing
- Long life LED (Rated at approximately 50,000 hrs.)
- Low power consumption
- Safety loop on rear
- Run all night – No duty cycle
- Multi-voltage: 100-240V, 50/60Hz
- Power Draw: 28.5W max
- Dimensions (LxWxH): 25" x 9" x 8" / 632.6 x 226.9 x 199mm
- Weight: 8 lbs. / 3.5 kg.

Specifications subject to change without notice.

