







SNI Software Uploader™

SKU# SNI211

The SNI Software Uploader™ is a battery powered hand held software uploader device used to update Elation compatible lighting fixtures. Easily upload a software update to an Elation lighting fixture by connecting the uploader to the fixture using a 3pin or 5pin DMX cable (not included). Elation software updates (not included) are stored on a MICRO SD card (included) and inserted into the uploader. SNI Software Uploader™ features an LCD display, 4 push button control panel, a MICRO SD card slot, 3pin and 5pin XLR DMX outputs, an On/Off switch, and includes a 12VDC external power supply, USB to MICRO SD card adapter, and blank MICRO SD card. Please contact Elation Service for details about available Elation fixture software updates.



PRODUCT SPECIFICATIONS

CONTROL / CONNECTIONS

4 Push Button Control Panel LCD Menu Display 3pin and 5pin DMX Out MICRO SD Card Slot Mini USB Input 12VDC Power Input

SIZE / WEIGHT

Length: 6.8" (173mm) Width: 3.4" (86mm) Vertical Height: 2.0" (51mm) Weight: 1.1 lbs. (0.5 kg)

ELECTRICAL

12VDC External Power Supply

INCLUDED ITEMS

MICRO SD Card USB to MICRO SD Card Adapter 5VDC External Power Supply

ELATION COMPATIBLE MODEL LIST

ARENA PAR
ARENA PAR ZOOM
ARENA Q7 ZOOM
PROTRON 3K LED STROBE
PROTRON 3K COLOR LED STROBE
SNIPER 2R
SNIPER PRO
TVL CYC RGBW
TVL PANEL DW

OPTIONAL ACCESSORIES

ORDER CODE	ITEM	
AC3PM5PFM	1 ft. (0.3m) 3pin Male to 5pin Female DMX Cable	
AC3PDMX5PRO	5 ft. (1.5m) 3pin PRO DMX Cable	
AC5PDMX5PRO	5 ft. (1.5m) 5pin PRO DMX Cable	
	Additional cable lenaths available	

