

ELATION® PLATINUM SPOT 15R B™				
SKU# EPS876 - DMX Channel Values / Functions (23 DMX Channels)				
Specifications are subject to change without any prior written notice.				
MODE / CHANNEL			VALUE	FUNCTION
STAND	BASIC	EXTEND		
1	1	1		PAN MOVEMENT [8 BIT]
			0-255	PAN Movement 540/630
2		2		PAN FINE MOVEMENT [16 BIT]
			0-255	Fine Control of PAN Movement
3	2	3		TILT MOVEMENT [8 BIT]
			0-255	TILT Movement 270
4		4		TILT MOVEMENT [16 BIT]
			0-255	Fine Control of TILT Movement
5	3	5		COLOR WHEEL
			0-18	OPEN / WHITE
			19-37	RED
			38-56	BLUE
			57-75	GREEN
			76-94	YELLOW
			95-113	UV FILTER
			114-127	CTO
			128-189	Color Macro Forward Rotation From FAST to SLOW
			190-193	NO Rotation
194-255	Color Macro Backwards Rotation From SLOW to FAST			
		6		COLOR WHEEL FINE ADJUSTMENT
			0-255	FINE Adjustment of Color Wheel To Any Position
6	4	7		ROTATING GOBOS, CONTINOUS ROTATION [GOBO WHEEL 1]
			0-9	OPEN
			10-19	Rotating Gobo 1
			20-29	Rotating Gobo 2
			30-39	Rotating Gobo 3
			40-49	Rotating Gobo 4
			50-59	Rotating Gobo 5
			60-69	Rotating Gobo 6
			70-79	Rotating Gobo 7
			80-89	Rotating Gobo 8
			90-104	Gobo 1 Shake SLOW to FAST
			105-119	Gobo 2 Shake SLOW to FAST
			120-134	Gobo 3 Shake SLOW to FAST
			135-149	Gobo 4 Shake SLOW to FAST
			150-164	Gobo 5 Shake SLOW to FAST
			165-179	Gobo 6 Shake SLOW to FAST
			180-194	Gobo 7 Shake SLOW to FAST
			195-209	Gobo 8 Shake SLOW to FAST
210-255	Gobo Wheel Rotation Forward from SLOW to FAST			
7	5	8		ROTATING GOBOS, INDEX ROTATION [GOBO WHEEL 1]
			0-127	Gobo Indexing
			128-189	Forward Gobo Rotation from FAST TO SLOW
			190-193	NO Rotation
			194-255	Backward Gobo Rotation from SLOW to FAST
		9		ROTATING GOBOS, FINE INDEX ROTATION [GOBO WHEEL 1]
			0-255	Rotating Gobo FINE Indexing

ELATION | **PLATINUM SPOT 15R B™** | dmX traits

ELATION® PLATINUM SPOT 15R B™
SKU# EPS876 - DMX Channel Values / Functions (23 DMX Channels)

Specifications are subject to change without any prior written notice.

MODE / CHANNEL			VALUE	FUNCTION
STAND	BASIC	EXTEND		
8	6	10		FIXED GOBOS [GOBO WHEEL 2]
			0-7	OPEN
			8-15	Gobo 1
			16-23	Gobo 2
			24-31	Gobo 3
			32-39	Gobo 4
			40-47	Gobo 5
			48-55	Gobo 6
			56-63	Gobo 7
			64-71	Gobo 8
			72-79	Gobo 9
			80-87	Gobo 10
			88-95	Gobo 11
			96-103	Gobo 12
			104-111	Gobo 13
			112-119	Gobo 14
			120-126	Gobo 1 Shake SLOW to FAST
			127-133	Gobo 2 Shake SLOW to FAST
			134-140	Gobo 3 Shake SLOW to FAST
			141-147	Gobo 4 Shake SLOW to FAST
			148-154	Gobo 5 Shake SLOW to FAST
			155-161	Gobo 6 Shake SLOW to FAST
			162-168	Gobo 7 Shake SLOW to FAST
			169-175	Gobo 8 Shake SLOW to FAST
			176-182	Gobo 9 Shake SLOW to FAST
			183-189	Gobo 10 Shake SLOW to FAST
			190-196	Gobo 11 Shake SLOW to FAST
			197-203	Gobo 12 Shake SLOW to FAST
204-210	Gobo 13 Shake SLOW to FAST			
211-217	Gobo 14 Shake SLOW to FAST			
218-255	Gobo Wheel Rotation from SLOW to FAST			
		11		FIXED GOBOS, FINE INDEX [GOBO WHEEL 2]
			0-255	Fixed Gobo FINE Indexing
9	7	12		3 FACET ROTATING PRISM, PRISM / GOBO MACROS
			0-31	OPEN
			32-127	3-Facet Rotating Prism
			128-135	Macro 1
			136-143	Macro 2
			144-151	Macro 3
			152-159	Macro 4
			160-167	Macro 5
			168-175	Macro 6
			176-183	Macro 7
			184-191	Macro 8
			192-199	Macro 9
			200-207	Macro 10
			208-215	Macro 11
			216-223	Macro 12
			224-231	Macro 13
			232-239	Macro 14
			240-247	Macro 15
248-255	Macro 16			

ELATION® PLATINUM SPOT 15R B™				
SKU# EPS876 - DMX Channel Values / Functions (23 DMX Channels)				
Specifications are subject to change without any prior written notice.				
MODE / CHANNEL			VALUE	FUNCTION
STAND	BASIC	EXTEND		
10	8	13		PRISM INDEXING, ROTATION
			0-127	Prism Indexing
			128-189	Forward Prism Rotation from FAST to SLOW
			190-193	NO Rotation
		14		PRISM FINE INDEXING
			0-255	FINE Prism Indexing
11	9	15		FOCUS
			0-255	Continuous Adjustment from NEAR to FAR
		16		FOCUS FINE
			0-256	Continuous FINE Adjustment
12	10	17		SHUTTER, STROBE
			0-31	Shutter CLOSED
			32-63	NO Function (Shutter OPEN)
			64-95	Strobe Effect SLOW to FAST
			96-127	NO function (Shutter OPEN)
			128-159	Pulse Effect In Sequences
			160-191	NO Function (Shutter OPEN)
			192-223	Random Strobe Effect SLOW to FAST
		18		DIMMER INTENSITY
13	11		0-255	Intensity 0 to 100%
		19		DIMMER INTENSITY FINE
			0-256	Dimmer Intensity FINE Adjustment
14	12	20		IRIS
			0-191	MAX to MIN Diameter
			192-223	Pulse Opening FAST to SLOW
			224-255	Pulse Closing SLOW to FAST
		21		IRIS FINE
			0-255	Iris FINE Adjustment
15	13	22		PAN / TILT MOVEMENT SPEED
			0-225	MAX to MIN Speed
			226-235	Blackout by Movement
			236-245	Blackout by ALL Wheel Changing
			246-255	NO Function
16	14	23		LAMP ON/OFF, RESET, INTERNAL PROGRAMS
			0-19	COLOR Change Normal
			20-29	COLOR Change To Any Position
			30-39	COLOR + GOBO Change To Any Position
			40-59	Lamp ON
			60-79	Lamp Switch OFF
			80-84	ALL Motor Reset
			85-87	SCAN Motor Reset
			88-90	COLOR Motor Reset
			91-93	GOBO Motor Reset
			94-96	SHUTTER + DIMMER Motor Reset
			97-99	Other Motor Reset
			100-119	Internal Program 1 (Scene 1-8)
			120-139	Internal Program 2 (Scene 9-16)
			140-159	Internal Program 3 (Scene 17-24)
			160-179	Internal Program 4 (Scene 25-32)
			180-199	Internal Program 5 (Scene 33-40)
200-219	Internal Program 6 (Scene 41-48)			
220-239	Internal Program 7 (Scene 49-56)			
		240-255	Music Control (Scene of Program 1)	

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
 323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands
 +31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu